

## Interoperability

This companion standard presents sets of parameters and alternatives from which subsets must be selected to implement particular telecontrol systems. Certain parameter values, such as the choice of "structured" or "unstructured" fields of the INFORMATION OBJECT ADDRESS of ASDUs represent mutually exclusive alternatives. This means that only one value of the defined parameters is admitted per system. Other parameters, such as the listed set of different process information in command and in monitor direction allow the specification of the complete set or subsets, as appropriate for given applications. This clause summarizes the parameters of the previous clauses to facilitate a suitable selection for a specific application. If a system is composed of equipment stemming from different manufacturers, it is necessary that all partners agree on the selected parameters.

The interoperability list is defined as in IEC 60870-5-101 and extended with parameters used in this standard. The text descriptions of parameters which are not applicable to this companion standard are strike-through (corresponding check box is marked black).

NOTE In addition, the full specification of a system may require individual selection of certain parameters for certain parts of the system, such as the individual selection of scaling factors for individually addressable measured values.

The selected parameters should be marked in the white boxes as follows:

- Function or ASDU is not used
- Function or ASDU is used as standardized (default)
- R Function or ASDU is used in reverse mode
- B Function or ASDU is used in standard and reverse mode

The possible selection (blank, X, R, or B) is specified for each specific clause or parameter.

A black check box indicates that the option cannot be selected in this companion standard.

### 1.1 System or device

(system-specific parameter, indicate definition of a system or a device by marking one of the following with "X")

- System definition
- Controlling station definition (Master)
- Controlled station definition (Slave)

### 1.2 Network configuration

(network-specific parameter, all configurations that are used are to be marked "X")

- |   |  |
|---|--|
| <input checked="" type="checkbox"/> Point-to-point          | <input checked="" type="checkbox"/> Multipoint-partyline |
| <input checked="" type="checkbox"/> Multiple point-to-point | <input type="checkbox"/> Multipoint-star                 |

### 1.3 Physical layer

(network-specific parameter, all interfaces and data rates that are used are to be marked "X")

Transmission speed (control direction)

| Unbalanced interchange<br>Circuit V.24/V.28<br>Standard | Unbalanced interchange<br>Circuit V.24/V.28<br>Recommended if >1 200 bit/s | Balanced interchange<br>Circuit X.24/X.27        |                                       |
|---|--|--|---------------------------------------|
| <input checked="" type="checkbox"/> 100 bit/s           | <input checked="" type="checkbox"/> 2 400 bit/s                            | <input checked="" type="checkbox"/> 2 400 bit/s  | <input type="checkbox"/> 56 000 bit/s |
| <input checked="" type="checkbox"/> 200 bit/s           | <input checked="" type="checkbox"/> 4 800 bit/s                            | <input checked="" type="checkbox"/> 4 800 bit/s  | <input type="checkbox"/> 64 000 bit/s |
| <input checked="" type="checkbox"/> 300 bit/s           | <input checked="" type="checkbox"/> 9 600 bit/s                            | <input checked="" type="checkbox"/> 9 600 bit/s  |                                       |
| <input checked="" type="checkbox"/> 600 bit/s           |  | <input checked="" type="checkbox"/> 19 200 bit/s |                                       |
| <input checked="" type="checkbox"/> 1 200 bit/s         |  | <input checked="" type="checkbox"/> 38 400 bit/s |                                       |

Transmission speed (monitor direction)

| Unbalanced interchange<br>Circuit V.24/V.28<br>Standard | Unbalanced interchange<br>Circuit V.24/V.28<br>Recommended if >1 200 bit/s | Balanced interchange<br>Circuit X.24/X.27        |                                       |
|---|--|--|---------------------------------------|
| <input checked="" type="checkbox"/> 100 bit/s           | <input checked="" type="checkbox"/> 2 400 bit/s                            | <input checked="" type="checkbox"/> 2 400 bit/s  | <input type="checkbox"/> 56 000 bit/s |
| <input checked="" type="checkbox"/> 200 bit/s           | <input checked="" type="checkbox"/> 4 800 bit/s                            | <input checked="" type="checkbox"/> 4 800 bit/s  | <input type="checkbox"/> 64 000 bit/s |
| <input checked="" type="checkbox"/> 300 bit/s           | <input checked="" type="checkbox"/> 9 600 bit/s                            | <input checked="" type="checkbox"/> 9 600 bit/s  |                                       |
| <input checked="" type="checkbox"/> 600 bit/s           |  | <input checked="" type="checkbox"/> 19 200 bit/s |                                       |
| <input checked="" type="checkbox"/> 1 200 bit/s         |  | <input checked="" type="checkbox"/> 38 400 bit/s |                                       |

**1.4 Link layer**

(network-specific Time during which repetitions are permitted (Trp) or number of repetitions parameter, all options that are used are to be marked "X". Specify the maximum frame length. If a non-standard assignment of class 2 messages is implemented for unbalanced transmission, indicate the Type ID and COT of all messages assigned to class 2.)

Frame format FT 1.2, single character 1 and the fixed time out interval are used exclusively in this companion standard.

Link transmission

- Balanced transmission
- Unbalanced transmission

Frame length

Maximum length L  
(control direction)

Maximum length L  
(monitor direction)

Time during which repetitions are permitted (Trp) or number of repetitions

Address field of the link

- Not present (balanced transmission only)
- One octet
- Two octets
- Structured
- Unstructured

When using an unbalanced link layer, the following ASDU types are returned in class 2 messages (low priority) with the indicated causes of transmission:

The standard assignment of ASDUs to class 2 messages is used as follows:

| Type identification | Cause of transmission |
|---------------------|-----------------------|
| 9, 11, 13, 21       | <1>                   |

A special assignment of ASDUs to class 2 messages is used as follows:

| Type identification | Cause of transmission |
|---------------------|-----------------------|
|                     |                       |
|                     |                       |
|                     |                       |
|                     |                       |

Note: (In response to a class 2 poll, a controlled station may respond with class 1 data when there is no class 2 data available).

## 1.5 Application layer

### Transmission mode for application data

Mode 1 (Least significant octet first), as defined in 4.10 of IEC 60870-5-4, is used exclusively in this companion standard.

### Common address of ASDU

(system-specific parameter, all configurations that are used are to be marked "X")

One octet                       Two octets

### Information object address

(system-specific parameter, all configurations that are used are to be marked "X")

One octet                       Structured  
 Two octets                       Unstructured  
 Three octets

### Cause of transmission

(system-specific parameter, all configurations that are used are to be marked "X")

One octet                       Two octets (with originator address).  
 Originator address is set to zero if not used

## Selection of standard ASDUs

### Process information in monitor direction

(station-specific parameter, mark each Type ID "X" if it is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

|                                     |      |   |           |
|-------------------------------------|------|---|-----------|
| <input checked="" type="checkbox"/> | <1>  | := Single-point information   | M_SP_NA_1 |
| <input checked="" type="checkbox"/> | <2>  | := Single-point information with time tag   | M_SP_TA_1 |
| <input checked="" type="checkbox"/> | <3>  | := Double-point information   | M_DP_NA_1 |
| <input checked="" type="checkbox"/> | <4>  | := Double-point information with time tag   | M_DP_TA_1 |
| <input checked="" type="checkbox"/> | <5>  | := Step position information  | M_ST_NA_1 |
| <input checked="" type="checkbox"/> | <6>  | := Step position information with time tag  | M_ST_TA_1 |
| <input checked="" type="checkbox"/> | <7>  | := Bitstring of 32 bit  | M_BO_NA_1 |
| <input checked="" type="checkbox"/> | <8>  | := Bitstring of 32 bit with time tag  | M_BO_TA_1 |
| <input checked="" type="checkbox"/> | <9>  | := Measured value, normalized value   | M_ME_NA_1 |
| <input checked="" type="checkbox"/> | <10> | := Measured value, normalized value with time tag                                     | M_ME_TA_1 |
| <input checked="" type="checkbox"/> | <11> | := Measured value, scaled value   | M_ME_NB_1 |
| <input checked="" type="checkbox"/> | <12> | := Measured value, scaled value with time tag   | M_ME_TB_1 |
| <input checked="" type="checkbox"/> | <13> | := Measured value, short floating point value   | M_ME_NC_1 |
| <input checked="" type="checkbox"/> | <14> | := Measured value, short floating point value with time tag                           | M_ME_TC_1 |
| <input checked="" type="checkbox"/> | <15> | := Integrated totals  | M_IT_NA_1 |
| <input checked="" type="checkbox"/> | <16> | := Integrated totals with time tag  | M_IT_TA_1 |
| <input type="checkbox"/>            | <17> | := Event of protection equipment with time tag  | M_EP_TA_1 |
| <input type="checkbox"/>            | <18> | := Packed start events of protection equipment with time tag                          | M_EP_TB_1 |
| <input type="checkbox"/>            | <19> | := Packed output circuit information of protection equipment with time tag            | M_EP_TC_1 |
| <input type="checkbox"/>            | <20> | := Packed single-point information with status change detection                       | M_SP_NA_1 |
| <input type="checkbox"/>            | <21> | := Measured value, normalized value without quality descriptor                        | M_ME_ND_1 |
| <input checked="" type="checkbox"/> | <30> | := Single-point information with time tag CP56Time2a                                  | M_SP_TB_1 |
| <input checked="" type="checkbox"/> | <31> | := Double-point information with time tag CP56Time2a                                  | M_DP_TB_1 |
| <input checked="" type="checkbox"/> | <32> | := Step position information with time tag CP56Time2a                                 | M_ST_TB_1 |
| <input checked="" type="checkbox"/> | <33> | := Bitstring of 32 bit with time tag CP56Time2a                                       | M_BO_TB_1 |
| <input checked="" type="checkbox"/> | <34> | := Measured value, normalized value with time tag CP56Time2a                          | M_ME_TD_1 |
| <input checked="" type="checkbox"/> | <35> | := Measured value, scaled value with time tag CP56Time2a                              | M_ME_TE_1 |
| <input checked="" type="checkbox"/> | <36> | := Measured value, short floating point value with time tag CP56Time2a                | M_ME_TF_1 |
| <input checked="" type="checkbox"/> | <37> | := Integrated totals with time tag CP56Time2a   | M_IT_TB_1 |
| <input type="checkbox"/>            | <38> | := Event of protection equipment with time tag CP56Time2a                             | M_EP_TD_1 |
| <input type="checkbox"/>            | <39> | := Packed start events of protection equipment with time tag CP56Time2a               | M_EP_TE_1 |
| <input type="checkbox"/>            | <40> | := Packed output circuit information of protection equipment with time tag CP56Time2a | M_EP_TF_1 |

Either ASDUs of the set <2>, <4>, <6>, <8>, <10>, <12>, <14>, <16>, <17>, <18>, <19> or of the set <30 –40> are used.

### Process information in control direction

(station-specific parameter, mark each Type ID "X" if it is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

|   |   |           |
|---|---|-----------|
| <input checked="" type="checkbox"/> <45> := | Single command                                | C_SC_NA_1 |
| <input checked="" type="checkbox"/> <46> := | Double command                                | C_DC_NA_1 |
| <input checked="" type="checkbox"/> <47> := | Regulating step command                       | C_RC_NA_1 |
| <input checked="" type="checkbox"/> <48> := | Set point command, normalized value           | C_SE_NA_1 |
| <input checked="" type="checkbox"/> <49> := | Set point command, scaled value               | C_SE_NB_1 |
| <input checked="" type="checkbox"/> <50> := | Set point command, short floating point value | C_SE_NC_1 |
| <input checked="" type="checkbox"/> <51> := | Bitstring of 32 bit                           | C_BO_NA_1 |

### System information in monitor direction

(station-specific parameter, mark with an "X" if it is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

|   |                       |           |
|---|-----------------------|-----------|
| <input checked="" type="checkbox"/> <70> := | End of initialization | M_EI_NA_1 |
|---|-----------------------|-----------|

### System information in control direction

(station-specific parameter, mark each Type ID "X" if it is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

|   |  |           |
|---|--|-----------|
| <input checked="" type="checkbox"/> <100>:= | Interrogation command                          | C_IC_NA_1 |
| <input checked="" type="checkbox"/> <101>:= | Counter interrogation command                  | C_CI_NA_1 |
| <input checked="" type="checkbox"/> <102>:= | Read command                                   | C_RD_NA_1 |
| <input checked="" type="checkbox"/> <103>:= | Clock synchronization command (option see 7.6) | C_CS_NA_1 |
| <input type="checkbox"/> <104>:=            | Test command                                   | C_TS_NA_1 |
| <input type="checkbox"/> <105>:=            | Reset process command                          | C_RP_NA_1 |
| <input type="checkbox"/> <106>:=            | Delay acquisition command                      | C_CD_NA_1 |



| Type identification |            | Cause of transmission |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
|---------------------|------------|-----------------------|---|---|---|---|---|---|---|---|----|----|----|----|----------|----------|----|----|----|----|
|                     |            | 1                     | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 20 to 36 | 37 to 41 | 44 | 45 | 46 | 47 |
| <13>                | M_ME_NC_1  |                       |   | X |   | X |   |   |   |   |    |    |    |    | X        |          |    |    |    |    |
| <14>                | M_ME_TC_1  |                       |   | X |   | X |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <15>                | M_IT_NA_1  |                       |   | X |   |   |   |   |   |   |    |    |    |    |          | X        |    |    |    |    |
| <16>                | M_IT_TA_1  |                       |   | X |   |   |   |   |   |   |    |    |    |    |          | X        |    |    |    |    |
| <17>                | M_EP_TA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <18>                | M_EP_TB_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <19>                | M_EP_TC_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <20>                | M_PS_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <21>                | M_ME_ND_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <30>                | M_SP_TB_1  |                       |   | X |   | X |   |   |   |   |    |    | X  |    |          |          |    |    |    |    |
| <31>                | M_DP_TB_1  |                       |   | X |   | X |   |   |   |   |    |    | X  |    |          |          |    |    |    |    |
| <32>                | M_ST_TB_1  |                       |   | X |   | X |   |   |   |   |    |    | X  |    |          |          |    |    |    |    |
| <33>                | M_BO_TB_1  |                       |   | X |   | X |   |   |   |   |    |    | X  |    |          |          |    |    |    |    |
| <34>                | M_ME_TD_1  |                       |   | X |   | X |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <35>                | M_ME_TE_1  |                       |   | X |   | X |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <36>                | M_ME_TF_1  |                       |   | X |   | X |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <37>                | M_IT_TB_1  |                       |   | X |   |   |   |   |   |   |    |    |    |    |          | X        |    |    |    |    |
| <38>                | M_EP_TD_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <39>                | M_EP_TE_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <40>                | M_EP_TF_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <45>                | C_SC_NA_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <46>                | C_DC_NA_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <47>                | C_RC_NA_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <48>                | C_SE_NA_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <49>                | C_SE_NB_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <50>                | C_SE_NC_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <51>                | C_BO_NA_1  |                       |   |   |   |   | X | X |   |   | X  |    |    |    |          |          | X  | X  | X  | X  |
| <70>                | M_EI_NA_1* |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <100>               | C_IC_NA_1  |                       |   |   |   |   | X | X |   |   |    |    |    |    |          |          | X  | X  | X  | X  |
| <101>               | C_CI_NA_1  |                       |   |   |   |   | X | X |   |   |    |    |    |    |          |          | X  | X  | X  | X  |
| <102>               | C_RD_NA_1  |                       |   |   |   | X |   |   |   |   |    |    |    |    |          |          | X  | X  | X  | X  |
| <103>               | C_CS_NA_1  |                       |   |   |   |   | X | X |   |   |    |    |    |    |          |          | X  | X  | X  | X  |
| <104>               | C_TS_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <105>               | C_RP_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <106>               | C_CD_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <107>               | C_TS_TA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <110>               | P_ME_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <111>               | P_ME_NB_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <112>               | P_ME_NC_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <113>               | P_AC_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <120>               | F_FR_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <121>               | F_SR_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <122>               | F_SC_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <123>               | F_LS_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <124>               | F_AF_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <125>               | F_SG_NA_1  |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |
| <126>               | F_DR_TA_1* |                       |   |   |   |   |   |   |   |   |    |    |    |    |          |          |    |    |    |    |

\* Blank or X only

## 1.6 Basic application functions

### Station initialization

(station-specific parameter, mark "X" if function is used)

Remote initialization

### Cyclic data transmission

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions)

Cyclic data transmission

### Read procedure

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions)

Read procedure

### Spontaneous transmission

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions)

Spontaneous transmission

### Double transmission of information objects with cause of transmission spontaneous

(station-specific parameter, mark each information type "X" where both a Type ID without time and corresponding Type ID with time are issued in response to a single spontaneous change of a monitored object)

The following type identifications may be transmitted in succession caused by a single status change of an information object. The particular information object addresses for which double transmission is enabled are defined in a project-specific list.

- Single-point information M\_SP\_NA\_1, M\_SP\_TA\_1, M\_SP\_TB\_1 and M\_PS\_NA\_1
- Double-point information M\_DP\_NA\_1, M\_DP\_TA\_1 and M\_DP\_TB\_1
- Step position information M\_ST\_NA\_1, M\_ST\_TA\_1 and M\_ST\_TB\_1
- Bitstring of 32 bit M\_BO\_NA\_1, M\_BO\_TA\_1 and M\_BO\_TB\_1 (if defined for a specific project)
- Measured value, normalized value M\_ME\_NA\_1, M\_ME\_TA\_1, M\_ME\_ND\_1 and M\_ME\_TD\_1
- Measured value, scaled value M\_ME\_NB\_1, M\_ME\_TB\_1 and M\_ME\_TE\_1
- Measured value, short floating point number M\_ME\_NC\_1, M\_ME\_TC\_1 and M\_ME\_TF\_1



## Station interrogation

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- |   |  |  |
|---|--|--|
| <input checked="" type="checkbox"/> global  |  |  |
| <input checked="" type="checkbox"/> group 1 | <input checked="" type="checkbox"/> group 7  | <input checked="" type="checkbox"/> group 13 |
| <input checked="" type="checkbox"/> group 2 | <input checked="" type="checkbox"/> group 8  | <input checked="" type="checkbox"/> group 14 |
| <input checked="" type="checkbox"/> group 3 | <input checked="" type="checkbox"/> group 9  | <input checked="" type="checkbox"/> group 15 |
| <input checked="" type="checkbox"/> group 4 | <input checked="" type="checkbox"/> group 10 | <input checked="" type="checkbox"/> group 16 |
| <input checked="" type="checkbox"/> group 5 | <input checked="" type="checkbox"/> group 11 |  |
| <input checked="" type="checkbox"/> group 6 | <input checked="" type="checkbox"/> group 12 |  |

Information object addresses assigned to each group must be shown in a separate table.

## Clock synchronization

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Clock synchronization
- Day of week used
- RES1, GEN (time tag substituted/ not substituted) used
- SU-bit (summertime) used

optional, see 7.6

## Command transmission

(object-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Direct command transmission
- Direct set point command transmission
- Select and execute command
- Select and execute set point command
- C\_SE ACTTERM used
  
- No additional definition
- Short-pulse duration (duration determined by a system parameter in the outstation)
- Long-pulse duration (duration determined by a system parameter in the outstation)
- Persistent output

## Transmission of integrated totals

(station- or object-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Mode A: Local freeze with spontaneous transmission
- Mode B: Local freeze with counter interrogation
- Mode C: Freeze and transmit by counter-interrogation commands
- Mode D: Freeze by counter-interrogation command, frozen values reported
  
- Counter read
- Counter freeze without reset
- Counter freeze with reset
- Counter reset
  
- General request counter
- Request counter group 1
- Request counter group 2
- Request counter group 3
- Request counter group 4

## Parameter loading

(object-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Threshold value
- Smoothing factor
- Low limit for transmission of measured values
- High limit for transmission of measured values

## Parameter activation

(object-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Act/deact of persistent cyclic or periodic transmission of the addressed object

## Test procedure

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Test procedure

## **File transfer**

(station-specific parameter, mark "X" if function is used).

File transfer in monitor direction

- Transparent file
- Transmission of disturbance data of protection equipment
- Transmission of sequences of events
- Transmission of sequences of recorded analogue values

File transfer in control direction

- Transparent file

## **Background scan**

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Background scan

## **Acquisition of transmission delay**

(station-specific parameter, mark "X" if function is only used in the standard direction, "R" if only used in the reverse direction, and "B" if used in both directions).

- Acquisition of transmission delay