

DA-720 Series Component Compatibility Guide

A list of peripheral components suitable for use with the DA-720 Series computers

2019/02/19 Version 2.2

Copyright Notice

©2018 Moxa Inc.
All rights reserved.

Trademarks

The MOXA logo is a registered trademark of Moxa Inc.
All other trademarks or registered marks in this manual belong to their respective manufacturers.

Disclaimer

Information in this document is subject to change without notice and does not represent a commitment on the part of Moxa.

Moxa provides this document as is, without warranty of any kind, either expressed or implied, including, but not limited to, its particular purpose. Moxa reserves the right to make improvements and/or changes to this manual, or to the products and/or the programs described in this manual, at any time.

Information provided in this manual is intended to be accurate and reliable. However, Moxa assumes no responsibility for its use, or for any infringements on the rights of third parties that may result from its use.

This document might contain unintentional technical or typographical errors. Changes are periodically made to the information herein to correct such errors, and these changes are incorporated into new editions of the publication.

Technical Support Contact Information

www.moxa.com/support

Moxa Americas

Toll-free: 1-888-669-2872
Tel: +1-714-528-6777
Fax: +1-714-528-6778

Moxa Europe

Tel: +49-89-3 70 03 99-0
Fax: +49-89-3 70 03 99-99

Moxa India

Tel: +91-80-4172-9088
Fax: +91-80-4132-1045

Moxa China (Shanghai office)

Toll-free: 800-820-5036
Tel: +86-21-5258-9955
Fax: +86-21-5258-5505

Moxa Asia-Pacific

Tel: +886-2-8919-1230
Fax: +886-2-8919-1231

1. Introduction

This document lists hardware components that are proven to provide the performance listed in the specification when used with the Moxa DA-720 Series embedded computers, or computers that share basic design features with the DA-720 Series. Moxa computers come with multiple peripheral options and are engineered to work with components having different hardware specifications. This flexibility could sometimes lead to compatibility issues. When used with the DA-720 Series embedded computers, peripherals from one manufacturer may not work as well as the ones made by another manufacturer. Moxa provides this list of DA-720 Series-compatible components, so that users can be certain of a reliable performance from the DA-720 Series, when used with the components listed in this document.

2. Testing Methods

To validate that a component meets the Moxa standards for quality and performance, the following five key compatibility tests are run:

- Ambient temperature burn-in
- Low temperature hard start
- Heat/humidity burn-in
- Cyclic high-low temperature burn-in
- Vibration test

Ambient Temperature Burn-In

The component is mounted on to a DA-720 computer and put through a series of stress tests at an ambient temperature of around 25°C, for a specified period of time. The duration of the test is determined based on the class of peripherals being tested.

Low Temperature Hard Start

The component is mounted on to an unpowered DA-720 computer and then the system is booted up at an extremely low temperature. The designated low temperature value depends on the computer model being tested.

Heat/Humidity Burn-In

The component is mounted on to a DA-720 computer, placed in a temperature- and humidity-controlled enclosure, and then put through the burn-in test for a specified period of time. The temperature, humidity, and time targets vary depending on the specification of the computer model used in the test.

Cyclic High-Low Temperature Burn-In

The component is mounted on to a DA-720 computer, placed in a temperature controlled enclosure, and then put through the burn-in test wherein the temperature is cyclically varied from very high to very low and back again, over a specified period of time. The target temperature range and the duration of the test can vary depending on the specification of the computer model used in the test.

Vibration Test

The component is mounted on to a DA-720 computer that is bound inside an electromagnetic vibrator, and then put through random vibration tests along three orthogonal axes: longitudinal, transverse, and vertical. The vibration tests are compliant with the EN50155/IEC61373 vibration standards.

3. Storage Endurance

Storage media, such as SSDs, CF cards, SD cards, Disk on Module, and Cfast, are composed of different electrical components. The main electrical components in these storage media, the NAND-flash memory and NAND-flash controller, impact the storage endurance and lifespan of the storage media.

NAND-Flash Memory Endurance

NAND-flash memories have a limit on the number of times they can be programmed and erased (P/E). The P/E cycle as well as the erase count of a NAND-flash memory can be used to determine this limit. For example, an SLC (single-level cell) flash memory has a 60,000 P/E cycle, an MLC (multi-level cell) flash memory has a 3,000 P/E cycle, and TLC NAND flash memories have P/E cycle values up to 1,000. Each flash memory type has a different endurance level, which is why the storage lifespan is based on the flash memory type. Storage that uses SLC type flash memory could have the best endurance level compared with the MLC type storage. SLC storage usually comes with a 5-year OEM warranty (the actual warranty period depends on the original manufacturer). MLC storage only comes with a 1- to 3-year warranty. The major differences between SLC and MLC are: (a) The SLC NAND flash has a lifespan that is around 20 times that of an MLC, and (b) The price can differ by a factor of 4 to 5. The SLC type of storage is recommended for systems that are expected to have high reliability, and for applications that need to frequently write data to a storage medium.

Terabytes Written (TBW)

TBW is the unit used to evaluate SSD endurance. In actual applications, storage is used for routine operations and data access. Therefore the physical P/E cycle is not appropriate for describing the total rewritable data capacity. The management efficiency of the storage controller also affects the total rewritable data capacity result. For these reasons, Joint Electron Device Engineering Council (JEDEC) has defined a standard for SSD endurance evaluation called JESD218, which uses TBW to measure the endurance of the storage memory. By referring to this TBW value, users can easily estimate the storage specification and select a suitable storage for real-life use cases. For example, when routine operations need a maximum of 20 GB and the expected storage lifespan is 3 years, the total rewritable data demand would be 21.9 TBW (20 GB x 365 x 3). In this case, a storage that has more than 21.9 TBW will meet the requirement. We recommend selecting a storage media with a TBW that is greater than the calculated value.

4. Declaration for Liability Exclusion

The specifications, warranty terms, and liability of items listed in this guide are the sole responsibility of the original manufacturers. Moxa does not take any responsibility in this regard. Please visit the manufacturers' official websites for up-to-date product information before purchasing the components.

5. Compatible Components

Peripheral components that have been tested and found suitable for use with the DA-720 Series computers are listed in this section. The following table lists the Test Codes and their descriptions:

Test Code	Description
A	The component has passed the ambient temperature verification test
B	The component has passed the low temperature verification test
C	The component has passed the heat/humidity verification test
D	The component has passed the cyclic high-low temperature verification test
E	The component has not been tested, but is similar to another component that has been tested in terms of its material and design.
F	The component has passed the vibration verification test

DRAM

Vendor	Memory Size	Moxa's PN	Vendor's PN	Interface	Chip Brand	Speed	Test Codes
DSL	4 GB	N/A	D4SP12081SH21B-XI	DDR4	ProMOS	2133 MHz	B, C, D
DSL	8 GB	1352110082027	D4SM12082SH21B-XI	DDR4	Micron	2133 MHz	B, C, D
DSL	16 GB	1352110162010	D4SM1G082SH21B-XI	DDR4	Micron	2133 MHz	B, C, D
InnoDisk	4 GB	1352110042096	M4S0-4GSSN5RG	DDR4	Samsung	2133 MHz	B, C, D

mSATA

Vendor	Storage Size	Moxa's PN	Vendor's PN	Flash Memory Brand	Flash Memory Spec	Controller	Firmware	Warranty	Warranty Exclusion	Test Codes
DSL	8 GB	1352030082214	DMBCMT008G0PS9I1F	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D
DSL	16 GB	1352030162215	DMBCMT016G1PS9I1F	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D
InnoDisk	16 GB	1352030162218	DEMSR-16GD08SWAQB	Toshiba	SLC	N/A	N/A	3 years	Endurance > 60,000	B, C, D
InnoDisk	32 GB	1352030322213	DEMSR-32GD08SWAQB	Toshiba	SLC	N/A	N/A	3 years	Endurance > 60,000	B, C, D
Transcend	64 GB	N/A	TS64GMSA370	N/A	MLC	N/A	N/A	N/A	N/A	B, C, D

SSD

Vendor	Storage Size	Moxa's PN	Vendor's PN	Flash Memory Brand	Flash Memory Spec	Controller	Firmware	Warranty	Warranty Exclusion	Test Codes
InnoDisk	128 GB	1352031282117	DES25-A28M41BW1DC	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D
InnoDisk	256 GB	1352032562112	DGS25-B56D81BW3QC	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D
InnoDisk	1 TB	1352030013211	DGS25-01TD81BWAQC	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D

HDD						
Vendor	Storage Size	Moxa's PN	Vendor's PN	Controller	Firmware	Test Code
HGST	1 TB	N/A	HCC541010B9E360	N/A	N/A	A