

# ABC-02 Series

*Configuration backup and restoration tool for managed switches and wireless AP/Bridge/Client products*



## Feature and Benefits

- Rugged, reliable design
- One-click backup and auto-load technology to reduce system downtime
- Powerful troubleshooting tool to record mass event logs
- Supports Moxa's managed Ethernet switches and wireless APs/bridges/clients
- One-click backup of system configurations using the RESET button
- Extend recorded entries of event logs
- Auto-backup of switch configuration files when any setting is changed
- Supports Moxa's managed Ethernet switches and wireless APs/bridges/clients products
- Plug-and-Play system configuration backup and restoration

## Certifications



## Introduction

The ABC-02 Series USB automatic backup configurators are designed for Moxa's products. The ABC-02 Series can save and load configuration files, back up event logs, and load firmware via the USB interface. The ABC-02 Series makes it easier to manage the backup of system parameters and perform configurations.

## Specifications

### Interface

Connector	USB 2.0 Type A
-----------	----------------

### Basic Operation

Storage Capacity	128 MB SLC type NAND Flash
------------------	----------------------------

### Power Parameters

Input Voltage	5 VDC (through USB interface)
---------------	-------------------------------

### Physical Characteristics

Housing	PVC molding
IP Rating	IP40
Dimensions	32.5 x 97 x 12 mm (1.28 x 3.82 x 0.47 in)
Weight	50 g (0.11 lb)
Installation	M4 screws (<4 mm)

## Environmental Limits

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature (package included)	-40 to 85°C (-40 to 185°F)
Ambient Relative Humidity	5 to 95% (non-condensing)

## Standards and Certifications

EMC	EN 55032 Class A
EMI	CISPR 32, FCC Part 15B Class A
EMS	IEC 61000-4-2 ESD: Contact: 4 kV; Air: 8 kV IEC 61000-4-3 RS: 80 MHz to 1 GHz: 10 V/m IEC 61000-4-4 EFT: Power: 2 kV; Signal: 1 kV IEC 61000-4-5 Surge: Power: 2 kV; Signal: 1 kV IEC 61000-4-6 CS: 10 V IEC 61000-4-8 PFMF

## Warranty

Warranty Period	5 years
Details	See <a href="http://www.moxa.com/warranty">www.moxa.com/warranty</a>

## Package Contents

Device	1 x ABC-01 Series automatic backup configurator
Documentation	1 x quick installation guide 1 x warranty card

## Ordering Information

Model Name	Connector	Storage	Operating Temp.
ABC-02-USB	USB 2.0 Type A	128 MB	0 to 60°C
ABC-02-USB-T	USB 2.0 Type A	128 MB	-40 to 75°C

© Moxa Inc. All rights reserved. Updated Nov 12, 2018.

This document and any portion thereof may not be reproduced or used in any manner whatsoever without the express written permission of Moxa Inc. Product specifications subject to change without notice. Visit our website for the most up-to-date product information.