

VPort 36 Modbus Address Table

Version 2.0

➤ Modbus Item Table

Address	Word (2 Bytes)	Item name	R/W	
0x0000	1	Vender ID	R	0x1393
0x0001	1	Unit ID	R	0x01
0x0002	1	Product Code	R	0x800E
0x0010	20	Vender Name	R	Moxa
0x0030	20	Product Name	R	VPort 36-1MP IP Camera
0x0050	1	Serial Number	R	
0x0051	2	Firmware Version	R	
0x0053	2	Release Date	R	
0x0055	3	MAC Address	R	
0x0080	1	DI Status	R	0x0000: Low 0x0001: High
0x0084	1	DO (Relay) Status	R/W	0x0000: Deactived 0x0001: Actived
0x0701	1	Record Status	R/W	R: 0: No record 1: recording W: 0: stop record 1: start record
0x0802	1	IVA Tamper Status	R/W	0x0000: No alert 0x0001: Alert
0x0803	1	IVA Learning Status	R	0x0000: No learning 0x0001: Is learning